
## Thermal links Thermal cutoff (TCO) Thermal fuse



### **Features and Benefits**


- Low Resistance
- Sealed Construction
- Radial and Axial Shape
- Rated Current: 1A~200A
- Compact size and Small size
- Function Temperature: 76C~221C
- One-time Over Temperature protection
- High accuracy of Cutoff temperature ±2C

# 587


## Thermal-links/Thermal cutoff/Thermal fuse

#### **Product Description**

SET<sub>®</sub> Alloy thermal cutoffs, defined as non-resettable, are single action devices that are widely used for the electrical equipments against over temperature. The thermal cutoffs are composed of the fusible alloy with low melting point and special resin, encapsulated in a plastic or ceramic housing. Under normal operated, the fusible alloy is joined by the two lead wires within the housing. When the thermal cutoff senses an abnormal heat and reach a preset temperature, the fusible alloy melts and disconnects the circuit completely with the aid of the special resin. Both Axial and Radial shapes are available, with rated current from 1A to 200A, Function temperature 76°C~221°C, certificated including UL, cUL, VDE,TUV,PSE, KTL, CCC and RoHS, REACH Compliant.



#### **Marking**





#### **Glossary of Terms**

- Thermal-link: also known as thermal cutoff or thermal fuse, all are the same in this context, function one only, non-resettable.
- Rated Function temperature (Tf):

The temperature of the Thermal-link which causes it to change its state of conductivity with a detection current up to 10mA as the only load.

Tolerance:  $+0^{\circ}$ C,  $-10^{\circ}$ C UL, VDE, IEC Standard

Tolerance: ±7℃ only PSE

• Fuse temperature (Fuse-temp):

The temperature is measured with silicone oil bath of which temperature is increased at the rate of  $0.5^{\circ}$ C~1°C/ min, with a detection current up to 10mA as the only load.

Holding temperature (Th):

The Max. temperature at which a TCO will not change its state of conductivity when conducting rated current for 168Hours.

Max. temperature limit (Tm):

The Max. temperature at which the TCO can maintain its mechanical and electrical properties without being impaired for 10 mins.

Rated current (Ir):

The current used to classify a Thermal-link, which is the Maximum current that thermal cutoffs allow to carry and are able to cutoff the circuit in safety.

• Rated voltage (Ur):

The voltage used to classify a Thermal-link, which is the Maximum voltage that is allowed to apply to the circuit in which the

thermal cutoff is used.

Transient overload current (Ip):

A direct current pulse train which the thermal-link is able to withstand without impairing its characteristics.

Agency	Agency Approvals												
Ag	jency	Standards	File Number	Category									
SN.	UL	UL60691 E214712		XCQM2									
<b>/</b>	cUL	CAN-CSA-E60691	E214712	XCQM8									
	TUV	EN60691	R50161772/R50112713/14/15/16/R50207621										
DVE	VDE	E EN60691 40004041/40017055/57/40018082											
⟨P.S⟩	PSE J60691		PSE09020139/40/41/42/43/44										
	KTL	K60691	SU05023-6001A/2A/3A/11001/2 /3										
<b>((()</b>	CCC	GB9816	2009010205350866/7/8/9744 2009010205346076/78/82/83 2009010205470986 2011010205470983/6										
ROHS	REACH • RoHS and REACH Compliant												

## 587


### Thermal-links/Thermal cutoff/Thermal fuse

#### **Safety Precautions**

- 1.Each thermal-link has specific Electrical and Temperature Rated and must be used with in the prescribed Rated. These Rated include Tf (Rated Function Temperature), Th or Tc (Holding Temperature), Tm (Maximum Temperature Limit), and the electrical Rated. Please see the technical data sheet.
- 2.For reason of safety that a thermal-link is a non-repairable item and that, in case of replacement an equivalent thermallink with the same catalogue number shall be used, mounted in exactly the same way.
- Install thermal-links so that their temperatures do not continuously exceed the Holding Temperature specified in the individual specification.
- 4. The end product should be designed so that thermal-link detects only intended heat source (radiant, convection, and / or conductance). For example, in a heater application, thermal-link should not be heated through lead wire which will accelerate the fusing off of the thermal-link, In case of a transformer or motor application, where the temperature should be controlled in a transformer or motor coil, and thermal-link should have good heat conductive contact with the transformer or motor coil.
- 5.It is recommended that using the dummy thermal-link having an internal thermocouple to select the proper temperature Rated and location of the thermal-link.
- 6.Do not locate the thermal-link on an assembly subjected to severe continuous vibration.
- 7.he end product should be tested to ensure that potentially abnormal conditions do not exposed the thermal-link to the temperature exceeding its Tm.
- 8.The seal or body must not be damaged, burned or over heated.
- 9. Mounting design of the thermal-links.
- 9.1Mount the thermal-link at the location where temperature rises evenly.
- 9.2Design the lead wire as long as possible and connect it in the way that tension or pressed torsion is not applied to the wire.

- 10.Lead wire bending.
- 10.1If the lead has to be used by bending it, bend it at approminimum away from the molded section, In the list below.

D	≪Ф1.0mm	>Ф1.0mm
L	≥3mm	≥5mm



- 10.2Use radio pinchers to bend the wire as shown in Fig.1 and not to damage the molded section of the case and the lead wire.
- 10.3Leads should not be cut, nicked, bended sharply, fractured or burned during forming or installation.
- 10.4Tangential forces on the leads must be avoided (i.e. pushing or pulling on the leads at angle to thermal-link body) as such forces may damage the seal of thermallinks.
- 11. The seal or body must not be damaged, burned or over heated.
- 12.Stress due to expansion and contraction of parts attached to the leads or body, vibration or other move ments of parts should be considered when designing the end prouct. A flexible or bent heater lead or a cold, low esistance heater lead should be used to connect to Thermal-link.
- 13.Resistance of connections should be monitored to en sure minimal resistance. Improper connections or secure may result in premature failure of the thermal-link. Sam ples of joints should be inspected to ensure adequate mechanical bonding of lead to connection wires. Improper connections can cause damage to the seal or other parts which may result in shorting or nuisance tripping of the devices due to the generation of excessive heat at a faulty high resistance junction.
- 14. Splices and terminations.
- 14.1If it is necessary to bare the lead of wire, there shall be



#### **Safety Precautions**


an arrangement that prevents deflection or damage of the thermal-link wires.


- 14.2Terminals or clamps should be of corrosion resistance materials.
- 14.3Appropriate free lengths of wire and sufficiently flexible wire connections should be used. Thermal-links and splices should be secured to prevent vibration or flexing of thermal-links and splices during normal operation.
- 15. Soldering of leads.
  - 15.1Soldering should be carried out within the soldering conditions listed in table 1.
  - 15.2Because the thermal element of thermal-link is a fusible alloy which connected with lead wires, improper soldering operation (too high soldering temperature, too long soldering time, too short lead wire used etc.) will cause thermal element damaged by the excessive heat transmit from the lead wire which may result in premature opening of thermal-link.
  - 15.3When soldering is required under severe conditions listed other than specified table 1, use a heat sink on thermal-link lead wire between solder joint and thermallink body.
  - 15.4Perform the soldering operation carefully so that the pull/push and twist tensions are not applied to thermallink body and lead wire.
  - 15.5After soldering leave it for natural cooling for longer than 20 sec. During this cooling time, never move the thermal-link body and lead wire.
- 16.Location of thermal-link with regard to wet application. If thermal-link is applied to coffeepot, hot-water heater, dryer, hygrostat, etc., locate the thermal-link at the position where thermal-link is protected from breakage by pilling water or other liquid and from damage by high humidity.
- 17.After Installation, the end construction shall comply with the appliance standard.
- 18.Read Standard Specification and Instruction Manual for use throughly.

Table 1. Soldering time (s)

	Max allowable soldering time (s)									
Length	Solder temperature									
10mm	20mm	30mm								
1*	2	3								
1*	2	3								
1*	3	5	400℃							
3	5	5								
4	6	7								
	10mm  1*  1*  1*  3	soldering time  Length of Lead w  10mm 20mm  1* 2  1* 2  1* 3  3 5	soldering time (s)       Length of Lead wire (L)       10mm     20mm     30mm       1*     2     3       1*     2     3       1*     3     5       3     5     5							

\* Need to add auxiliary heat conduction for not damage the thermal fuse unexpectedly.






**Specifications** 

K Series Ir: 2A





Dimensions	

	Α	В	С	D(Ф)	Е	F*	
Ī	5.8±0.5	5.8±0.5	2.3±0.2	$0.54 \pm 0.05$	70±3	3.7±0.5	

Note: The dimension F is measured from the root of leadwires.

#### **Key Features**

- Plastic case
- One-time over temperature protection
- Alloy type Thermal-link
- •Environmental-friendly products

#### **Applications**

- Motor
- Battery
- Transformer
- Power supplies
- Lamps and lanterns
- Home electrical appliances

#### Customized

Other temperatures can be customized such as: $85^{\circ}\text{C},90^{\circ}\text{C},92^{\circ}\text{C},95^{\circ}\text{C},97^{\circ}\text{C},100^{\circ}\text{C},103^{\circ}\text{C},108^{\circ}\text{C},117^{\circ}\text{C},120^{\circ}\text{C},127^{\circ}\text{C},And etc.}$  The length of leadwires can be customized as required.

#### **Packing Information**

QTY:50Kpcs/Carton Carton Size: 44cm×30cm×26cm.

	Model	Tf (°C)	Fuse- Temp (°C)	Th (℃)	Tm (°C)	Ir (A)	Ur (V)		: <b>4</b>	-		<u> </u>	<b>®</b>		RoHS
8	K0	76	73±2	53	200	2	250AC	UL •	cUL	PSE	VDE	TUV	CCC	KIL	RoHS
							250AC	•	•	•	•		•	•	•
	K18	86	81±2	61	200	2	60DC	•	•						•
	K1	102	98±2	79	200	2	250AC	•	•	•	•	•	•	•	•
	KI	102	90±2	79	200	2	60DC	•	•						•
	K2	115	111±2	91	200	2	250AC	•	•	•	•	•	•	•	•
						_	60DC	•	•						•
	K3	125	121±2	100	200	2	250AC	•	•	•	•	•	•	•	•
							60DC	•	•						•
	K4	130	125±2	106	200	2	250AC	•	•	•	•	•	•	•	•
	K8	133	130±2	111	200	2	250AC	•	•	•	•		•	•	•
	K5	135	130±2	111	200	2	250AC	•	•	•	•		•	•	•
	K9	136	131±2	112	200	2	250AC	•	•	•	•		•	•	•
	K6	145	140±2	121	200	2	250AC	•	•	•	•		•	•	•
	K7	150	145±2	126	200	2	250AC	•	•	•	•	•	•	•	•
	K16	160	154±2	135	200	2	250AC			•			•		•
	K32	205	199±3	169	250	2	250AC	•	•			•	•		•
	K31	221	218±2	188	250	2	250AC	•	•			•	•		•

#### **Agency Approvals**

UL/cUL: E214712VDE: 40017055TUV: R50161772/779


PSE: 09020139/40/41/42/43/44

• CCC: 2009010205346083

KTL: SU05023-6001A/6002A/6003B

RoHS & REACH Compliant


#### Performance Curve




Thermal-links/Thermal cutoff/Thermal fuse

This is an illustrated curve for the model K series, describing the open time VS Multi-times rated current in the condition of the room temperature 25°C.


(This curve is for reference only)






This is an illustrated curve for the model K series, The temperature is measured with silicone oil bath of which temperature is increased at the rate of 0.5 °C~1°C/ min, with a detection current up to 10mA as the only load.


(This curve is for reference only)



Frequency: Concentration ratio of real opening temperature measured in the preset conditions.

**Specifications** 





Dimensions (mm)

Α	В	С	D(Ф)	Е	F*	
$5.8 \pm 0.5$	$5.8 \pm 0.5$	$2.3 \pm 0.2$	$0.54 \pm 0.05$	70±3	$3.7 \pm 0.5$	

Note: The dimension F is measured from the root of leadwires.

#### **Key Features**

- Plastic case
- One-time over temperature protection
- Alloy type Thermal-link
- Environmental-friendly products

#### **Applications**

- Motor
- Battery
- Transformer
- Power supplies
- Lamps and lanterns
- Home electrical appliances

#### Customized

Other temperatures can be customized such as:85°C,90°C,92°C, 95°C,97°C, 100°C,103°C,108°C, 117°C,120°C, 127°C,And etc. The length of leadwires can be customized as required.

#### **Packing Information**

QTY:50Kpcs/Carton
Carton Size:44cm×30cm×26cm

	Model	Tf (℃)	Fuse- Temp (°C)	Th (℃)	Tm (℃)	Ir (A)	Ur (V)	<b>91</b> *	<b>;}\</b> *	ľ	Å. VDE		<b>©</b>		RoHS
ts	X0	76	73±2	53	200	3	250AC	•	•	•	VDE	100	•	KIL	•
	X18	86	81±2	61	200	3	250AC	•	•	•	•		•	•	•
	A10	00	01±2	01	200	3	60DC	•	•						•
	X1	102	98±2	79	200	3	250AC	•	•	•	•		•	•	•
	71.				200		60DC	•	•						•
	X2	115	111±2	91	200	3	250AC	•	•	•	•		•	•	•
							60DC	•	•						•
	X3 125	125	121±2	100	200	3	250AC	•	•	•			•		•
							60DC	•	•						•
	X4	130	125±2	106	200	3	250AC	•	•	•	•		•	•	•
:-	X8	133	130±2	111	200	3	250AC	•	•	•	•		•	•	•
,	X5	135	130±2	111	200	3	250AC	•	•	•	•		•	•	•
e	Х9	136	131±2	112	200	3	250AC	•	•	•	•		•	•	•
C	X6	145	140±2	121	200	3	250AC	•	•	•	•		•	•	•
	X7	150	145±2	126	200	3	250AC	•	•	•	•		•	•	•
	X16	160	154±2	135	200	3	250AC			•			•		•
l	X32	205	199±3	169	250	3	250AC	•	•			•	•	•	•
	X31	221	218±2	188	250	3	250AC	•	•			•	•	•	•

#### **Agency Approvals**


UL/cUL: E214712VDE: 40017055TUV: R50161779

PSE: 09020139/40/41/42/43/44

CCC: 2009010205346083KTL: SU05023-6001A/6003B


RoHS & REACH Compliant


#### Performance Curve



This is an illustrated curve for the model X series, describing the open time VS Multi-times rated current in the condition of the room temperature 25°C.


(This curve is for reference only)





This is an illustrated curve for the model X series, The temperature is measured with silicone oil bath of which temperature is increased at the rate of 0.5°C~1°C/ min, with a detection current up to 10mA as the only load.


(This curve is for reference only)



Frequency: Concentration ratio of real opening temperature measured in the preset conditions.

**Specifications** 





#### Dimensions (mm)

Α	В	С	D(Φ)	Е	F*	
$6.6 \pm 0.5$	$7.0 \pm 0.5$	$2.7 \pm 0.3$	$0.80 \pm 0.05$	70±3	$4.0 \pm 0.5$	

Note: The dimension F is measured from the root of leadwires.

#### **Key Features**

- Plastic case
- One-time over temperature protection
- Alloy type Thermal-link
- Environmental-friendly products

#### **Applications**

- SPD
- Battery
- Transformer
- Power supplies
- Lamps and lanterns
- Home electrical appliances

#### Customized

Other temperatures can be customized such as:85°C,90°C,92°C, 95°C,97°C, 100°C,103°C,108°C, 117°C,120°C, 127°C,And etc. The length of leadwires can be customized as required.

#### **Packing Information**

QTY:30Kpcs/Carton
Carton Size:4cm×30cm×26cm.

ts	Model	Tf (℃)	Fuse- Temp (°C)	Th (℃)	Tm (℃)	Ir (A)	Ur (VAC)	In 8/20µs (15Times) (KA)	Imax 8/20µs (1Time) (KA)	<b>91</b> 1°	<b>. FN</b> °	•	<b>₽</b>			RoHS
	Y0	76	73±2	53	200	5	250	2	4	•	•	•		•		•
	Y18	86	81±2	61	200	5	250	2	4	•	•	•		•		•
	Y1	102	98±2	77	200	5	250	3	6	•	•	•		•		•
	Y2	115	111±2	89	200	5	250	3	6	•	•	•	•	•	•	•
	Y3	125	121±2	98	200	5	250	3	6	•	•	•	•	•	•	•
-	Y4	130	125±2	103	200	5	250	3	6	•	•	•	•	•	•	•
,	Y8	133	130±2	108	200	5	250	3	6	•	•	•	•	•	•	•
е	Y9	136	131±2	111	200	5	250	3	6	•	•	•	•	•	•	•
	Y6	145	140±2	118	200	5	250	3	6	•	•	•				•
	Y7	150	145±2	123	200	5	250	3	6	•	•	•	•	•	•	•
	Y16	160	154±2	133	200	5	250	3.5	7			•		•		•

#### **Agency Approvals**

UL/cUL: E214712VDE: 40017057

PSE: 09020139/40/41/42/43/44


• CCC: 2009010205346082

KTL: SU05023-6001A/6002A/6003B

RoHS & REACH Compliant





#### Performance Curve



This is an illustrated curve for the model Y series, describing the open time VS Multi-times rated current in the condition of the room temperature 25°C.


(This curve is for reference only)





This is an illustrated curve for the model Y series, The temperature is measured with silicone oil bath of which temperature is increased at the rate of 0.5°C~1°C/ min, with a detection current up to 10mA as the only load.

(This is curve for reference only)



Frequency: Concentration ratio of real opening temperature measured in the preset conditions.